Animal Ear Thermometer Model: Q-Temp

Features:

Q-Temp is an instant infrared ear thermometer designed for pets and animals by Shinova. It measures an body temperature from the ear in only one-second, which has been clinically proven accurate on dogs and cats.

Q-Temp is a really a good helper for pet hospitals, groomers, per owners, breeders, working dog owners, kennels, search and rescue, etc.



Applications: For Occasions: When your pet is sick For breeding and pregnancy After surgery After vaccinations After injury or trauma

For Animals: Dogs Cats Puppies Kittens Rabbits Ferrets Chinchillas Guinea pigs

Specifications:

	-	
IS:	Measurement time	In one second
oet is sick	Temperature measurement range	34°C to 42.2°C (93.2°F to 108°F)
; and pregnancy / ations or trauma	Temperature scale	°C or °F
	Display resolution	0.1°C or 0.1°F
	Data memory	Last memory can be stored
	Audible alarm	Built-in audible alarm
	Auto power off	If no button is pressed within 60 seconds
	Battery	CR 2032, 3V
	Ambient operating condition	±0.2°C(±0.4°F) 35°C to 42°C (95°F to 107.6°F)
		±0.3°C(±0.5°F) <35°C (95°F) or >42°C (107.6°F)
	Laboratory accuracy against an infrared	10°C to 40°C (50°F to 104°F)
	source	
	Storage temperature range	-20°C to 55°C (-4°F to 131°F)
	Dimension	135mmx64mmx26mm (After folding)
	Weight	Approx 75g (battery included)

Animal Infrared Thermometer Model: G-Temp

Features:

- 1) High precision non-contact animal temperature measurement
- 2) Unit °C or °F selectable
- 3) Alarm temperature adjustable
- 4) Buzzing alarm function (Buzzer can be set to on or off)
- 5) LCD with backlight is suitable for weak illumination
- 6) LED Laser signal is suitable for the usage point to the measure part
- 7) Automatic adaptable range
- 8) Store the recent 32 measuring data
- 9) Automatic data storage and shut down

Specifications:

0.1°C (0.1°F)
0-50°C (32~122°F)
10~40°C (50~104°F)
≤85%
Two #7 battery
158*90*37mm
Gross 267g, Net 137g
32.0-45°C
0~100°C
±0.4°C (0.7°F)
±1.0°C (1.8°F)
5~15cm (2~5.9inch)
8 seconds

